



FRANCIS WALL LIGHT BULKHEAD INSTALLATION GUIDE

Product codes: 09609, 09080, 09312

INSTRUCTIONS FOR USE AND INSTALLATION

GENERAL INFORMATION & TECHNICAL SPECIFICATIONS

This product has been made in the EU

- 230V ~ 50Hz
 - Class I
 - GX53 lamp holder
 - Not intended for mesh connection.
 - Intended for connection to fixed wiring.
 - Double-protection 3G1.5 power cable should be used for the connection of the light fixture.
 - Power cable not included.
 - Terminal block included.
-

GENERAL INFORMATION ABOUT SAFETY

- Before any work turn off the mains supply.
- Installation should only be carried out by a qualified electrician, who should be aware of the current Regulations on Internal & External Installations.
- In case of glass breakage, replace immediately.

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: sales@navigatorlighting.co.uk | Website: navigatorlighting.co.uk

V1 24.10.2025



- Lightbulb Wattage should never exceed the Wattage (W) indicated on the label or the packaging of the light fixture.
 - The fitting should be connected to a line protected by a differential current circuit, while the nominal persistent operating current should not exceed 30mA (leakage relay).
-

Included in the package:

1 light fixture
2 sets of wall-plugs and screws
2 rubber washers
2 plastic washers
3 insulation hoses
1 rubber inlet for the power cable

LIGHT FIXTURE INSTALLATION

A. MOUNTING THE LIGHT FIXTURE

- Unscrew the cage and remove the glass from the base of the light fixture.
 - Using the base of the light fixture as an installation guide, mark the surface on which you wish to mount it.
 - Drill holes on the mounting surface and insert the wall-plugs.
 - Place the rubber cable inlet to the light fixture's base.
 - Screw the base of the light fixture onto the mounting surface. To ensure the insulation of the fixture, use the plastic washers and rubber retainers when screwing the screws.
 - Re-fix the lamp cage.
-



B. CONNECTING THE POWER CABLE

- Cover the wires with supplied insulating hoses. Connect the **live (brown)** and **neutral (blue)** to the terminal block and connect the **earth wire (yellow)** to the base of the light fixture (using the bonding screw), using the supplied screw and M4 washer.
 - Same goes for the lamp holder.
 - Fit the glass and lamp cage to the body of the light fixture.
 - Turn on the power supply.
-

C. REPLACING THE LIGHTBULB

- Turn off the mains supply.
 - Do not try to replace the lightbulb unless it has completely cooled down as it may cause burns and injury.
 - Remove the glass and cage.
 - Detach and lift the lightbulb gently.
 - Avoid touching the lightbulb with bare hands.
 - Make sure the gasket is clean, as it may reduce waterproofness.
 - When replacing the lightbulb, insert it very carefully while the lightbulb is still in the lamp holder's base.
 - After connecting with electricity, replace the lightbulb's cover to maintain the impermeability of the fixture.
-

The manufacturer bears no responsibility for any injury or damage resulting from incorrect installation or use of the product.