



---

## MARLINSPIKE SPOT LIGHT INSTALLATION GUIDE

**TYPE:** 09788, 09789, 09790

### INSTRUCTIONS FOR USE AND INSTALLATION

#### GENERAL INFORMATION & TECHNICAL SPECIFICATIONS

- 230V ~ 50Hz
- Class I
- GU10 porcelain socket
- Not intended for mesh connection
- Intended for connection to fixed wiring
- 3G1.5 power cord should be used for the connection of the light fixture
- Power cord not included

#### GENERAL INFORMATION ABOUT SAFETY

- Before any work turn off the mains supply
- Installation should only be carried out by a qualified electrician, who should be aware of the current Regulations on Internal & External Installations
- In case of glass breakage, replace immediately
- Never exceed the Watts (W) specified on the light fixture
- Lamp power should not exceed the power indicated on the label of the fixture or on the package
- The product should be connected to a line protected by a differential current circuit, while the nominal persistent operating current should not exceed 30mA (leakage relay)

#### Included in the package:

1 Light fixture

#### LIGHT FIXTURE INSTALLATION

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 24.10.2025



## **A. FIXING THE POST ON THE GROUND AND CONNECTING THE POWER CORD**

- Unscrew the body of the light fixture from its base.
- Pass the power cord through the cable entry.
- Connect the line (L, brown) and neutral (N, blue) wires to the cable clamp and the grounding wire (G, yellow) to the base of the light fixture next to the grounding symbol  $\equiv$ .
- Screw the body of the light fixture onto the base.
- Remove the glass cover(s) of the light fixture by unscrewing it.
- Remove the spring(s) used for holding the lightbulb in place.
- Insert the GU10 lightbulb(s) into the GU10 socket.
- Replace the spring(s) and the glass cover(s) of the light fixture.
- To stabilize the light fixture at the desired tilt, tighten the screws on the sides of the base.
- Pin the light fixture into the ground.
- Turn on the power supply.

## **B. REPLACING THE LIGHTBULB**

- Turn off the mains supply.
- Do not try to replace the lightbulb unless it has completely cooled down as it may cause serious burns on the skin.
- Remove the glass cover(s) of the light fixture by unscrewing it.
- Remove the spring(s) used for holding the lightbulb in place.
- Remove the old GU10 lightbulb(s) from the socket by gently pulling it out.
- Do not touch the lightbulb with bare hands.
- Always use clean protective gloves when handling a lightbulb.
- Use a clean towel to clean the bulb in case you touch it accidentally.
- Insert the GU10 lightbulb(s) into the GU10 socket.
- Replace the spring(s) and the glass cover(s) of the light fixture.
- Turn on the power supply.

**The manufacturer bears no responsibility for any injury or damage resulting from incorrect installation or use of the product.**

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 24.10.2025