



---

## MINI COMPASS GUARD BULKHEAD INSTALLATION GUIDE

**Product codes:** 09006, 09004, 09308

---

### INSTRUCTIONS FOR USE AND INSTALLATION, GENERAL INFORMATION & TECHNICAL SPECIFICATIONS

#### PRODUCTS MANUFACTURED IN EU

- 230V ~ 50Hz
- Class I
- G9 lamp holder
- Not intended for connection to fixed wiring.
- Rubber double-insulation H05RN-F 3G1.5 power cable should be used for the connection of the light fixture.
- Power cable not included

#### GENERAL INFORMATION ABOUT SAFETY

- Before any work turn off the mains supply.
- Installation should only be carried out by a qualified electrician, who should be aware of the current Regulations on Internal & External Installations.
- In case of glass breakage, replacement must be made immediately.
- Lightbulb Wattage should never exceed the Wattage (W) indicated on the label of packaging of the product.
- The product should be connected to a line protected by a differential current circuit, while the nominal persistent operating current should not exceed 30mA (leakage relay).

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 28.10.2025



# Navigator

**Included in the package:**

- 1 light fixture
- 1 plastic insulating cover for the lamp holder
- 2 sets of wall-plugs and screws
- 1 instruction sheet

**LIGHT FIXTURE INSTALLATION****A. MOUNTING THE LIGHT FIXTURE**

- Unscrew the cage and remove the glass from the body of the light fixture.
- Using the base of the light fixture as an installation holder, mark the surface on which you wish to mount it.
- Drill holes to mount the fixture and fix the base of the light fixture to it, using the supplied wall-plugs and screws.

**B. CONNECTING THE POWER CABLE**

- Remove the lamp holder and the terminal block from the fixture.
- Pass the power cable through the cable tunnel.
- Connect the power cable to the terminal block.
- Fix the live wire (brown) and the neutral (blue) wires to the lamp holder and the grounding wire (yellow and white) of the fixture next to the grounding symbol (⊕), using the supplied screw and M4 washer.
- Fit the lamp holder and the terminal block on the base of the light fixture.
- Tighten the cable gland.
- Connect the power supply wire over the lamp holder.
- Fit the glass and fasten the cage to the body of the light fixture.
- Turn on the power supply.

**C. REPLACING THE LIGHTBULB**

- Turn off the mains supply.
- Do not try to remove the bulb immediately as it may cause burns on the skin.

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 28.10.2025



# Navigator

- Unscrew the cage.
- Remove the glass.
- Unscrew the lightbulb gently.
- Do not touch the lightbulb with bare hands.
- Use a dry cloth to hold the lightbulb.
- Replace the lightbulb with the same kind and wattage.
- Insert the new lightbulb very carefully while it is still in the lamp holder.
- Before feeding the power supply, clean the lightbulb.
- Screw the glass and cage back on.

**The manufacturer bears no responsibility for any injury or damage resulting from incorrect installation or use of the product.**

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 28.10.2025